Inward Connections

StepEQ
Program Equalizer

Features of the 500 series StepEQ:

- Hi Mid Band Controls
  Frequency switch selects 4K, 8K, 12K, 16K, 20KCS
  -16dB cut level
- Mid Band Peak Controls
  Frequency switch selects 1K, 2K, 3K, 4K, 5K, 8K, 10K, 12K, 16KCS
  Bandwidth control
  +14dB boost level
- Lo Band Shelf Controls
  Frequency switch selects 20Hz, 30Hz, 60Hz, 90Hz, 120Hz
  -16dB cut level
  +14dB boost level
- Bypass switch
- SPA690 all discrete legendary amp blocks
- Differential balance input transformer
- Balance output transformer
- Double-wide module fits in standard 500 series rack slots configuration mechanically and electrically



Actual size 5.25" x 3"

Specifications:

• Input Impedance	600 ohms balance
• Output Impedance	600 ohms balance
• Frequency Response	+/- 0.5dB to 50KHz
• Output Signal to Noise	-95dB or greater
• THD + Noise	.01%@1KHz/+4dBu

7710 Maestro Avenue, West Hills, CA 91304
tel: 818-883-9012 fax: 818-883-5049
email: sfirlotte@socal.rr.com