| Item no. | Sch.ref. | Description | Qty. | EAA Part number |
|---|---|---|---|---|
| 852 | B 1 | Blower, 45 l/s, 115VAC, 50/60 Hz, 20W, ref. 4600N | 1 | 4600N |
| 853 | BB 1 | Bus bar, grounding, ref. 33.318D | 1 | 33.318D |
| 855 | C 1 | Capacitor, electrolytic, case 72x114mm, 22000 to 30000 mF, 100V | 4 | 374579 |
| 856 | C 2 | Ident. to C1 | | |
| 857 | C 3 | Ident. to C1 | | |
| 858 | C 4 | Ident. to C1 | | |
| 859 | C 13 | Capacitor, film, 0.1 to 0.22mF, 250V | 2 | |
| 860 | C 14 | Ident. to C13 | | |
| 861 | CP 1 | Clamp for power cord, ref. DM8 | 1 | DM8 |
| 863 | DB 1 | Diode bridge, 25A 400V, ref. FB3504 | 3 | FB3504 |
| 864 | DB 2 | Ident. to DB1 | | |
| 865 | DB 3 | Ident. to DB1 | | |
| 867 | F 1 | Fuse, 1/4" x 1 1/4", slo-blow, 20A, ref. 313020 | 2 | 313020 |
| 868 | F 2 | Ident. to F1 | | |
| 869 | F 3 | Fuse, 1/4" x 1 1/4", slo-blow, 25A, ref. 326025 | 4 | 326025 |
| 870 | F 4 | Ident. to F3 | | |
| 871 | F 5 | Ident. to F3 | | |
| 872 | F 6 | Ident. to F3 | | |
| 873 | FH1 | Fuse holder, ref. 345603 | 2 | 345603 |
| 874 | FH2 | Ident. to FH1 | | |
| 875 | FH3 + FH4 | Fuse holder, ref. 354802-GY | 2 | 354802-GY |
| 876 | FH5 + FH6 | Ident. to FH3+FH4 | | |
| 878 | PC 1 | Power cord, HO7-RNF 3x2.5mm2 | 1 | HO7-RNF-3x2.5 |
| 880 | SW 1 | Switch, toggle, 1 section, ref. 5636A16 | 1 | 5636A16 |
| 882 | T 1 | Transformer, 115/240 VAC, 50/60 Hz, ref. AD32C1TM | 1 | AD32C1TM |
| 883 | TB1 + TB2 | Terminal block assembly, including: | 1 | TB1+TB2 |
| 884 | | - 4 Terminal block, ref. 261-301 | | |
| 885 | | - 1 End plate, ref. 261-361 | | |
| 886 | TB 3 | Terminal block assembly, including: | 1 | TB3 |
| 887 | | - 2 Terminal block, ref. 262-301 | | |
| 888 | | - 1 End plate, ref. 262-361 | | |
| 889 | TSW 1 | Thermo-switch, normally open contact, ref. 65-0-98-22-040-030 | 2 | 65-0-98-22-040-030 |
| 890 | TSW 2 | Ident. to TSW1 HEITO 50°/35° ±3° MJE (ou M16) | | |
| 892 | | Transformer assembly, | | AD32C1TM/ASSY. |
| 893 | | (including: transformer, transformer brackets and hardware) | | |
| 895 | | Power capacitors assembly | | 374579/ASSY. |
| 896 | | (including capacitors C1 to C4, bus bar BB1 and connect. cables) | | |

| Item no. | Sch.ref. | Description | Qty. | EAA Part number |
|---|---|---|---|---|
| | | | | |
| 902 | Y 3 | Transformer, lower bracket, ref. 23.292E | 1 | 23.292E |
| 903 | Y 4 | Transformer, upper bracket, ref. 23.293E | 1 | 23.293E |
| | | | | |
| | | | | |
| | | | | |
| | | Hardware used to secure blower B1 | | |
| 908 | Z 5 | Machine screw, metric, TC-4x50 | 4 | TC4x50 |
| | | | | |
| | | | | |
| | | Hardware used to secure bus bar BB1 | | |
| 912 | Z 6 | Machine screw, metric, TC-4x10 | 4 | TC4x10 |
| 913 | Z 7 | Lockwasher, ZI4 | 8 | ZI4 |
| 914 | Z 8 | Hex. nut, metric, Hm4 | 4 | Hm4 |
| 915 | X 12 | Tabs, grounding terminals, ref. 30086 | 1 | 30086 |
| | | | | |
| | | | | |
| | | Hardware used to secure electrolytic power capacitors C1 to C4 | | |
| 919 | Y 5 | Capacitor bracket, ref. 33.299B | 2 | 33.299B |
| 920 | Z 9 | Hex. machine screw, metric, TH5x50 | 2 | TH-5x50 |
| 921 | Z 10 | Washer, flat, M5x12 | 2 | M5x12 |
| | | | | |
| | | | | |
| | | Hardware used to secure diode bridges DB1 to DB3 | | |
| 925 | Z 11 | Machine screw, metric, TFHC5x20 | 3 | TFHC5x20 |
| 926 | Z 12 | Hex. nut, metric, Hm5 | 3 | Hm5 |
| | | | | |
| | | | | |
| | | Hardware used to secure fuse holders FH3 to FH6 | | |
| 930 | Z 13 | Pop rivet, 3.2x8mm | 4 | TAP/046 |
| | | | | |
| | | | | |
| | | Hardware used to secure toggle switch SW1 | | |
| 934 | Z 4 | Dress nut, ref. U500 | 1 | U500 |
| | | | | |
| | | | | |
| | | Hardware used to secure transformer T1 | | |
| 938 | Z 14 | Machine screw, metric, TFHC5x12 | 6 | TFHC5x12 |
| 939 | Z 15 | Hex. machine screw, metric, TH6x80 | 4 | TH6x80 |
| 940 | Z 16 | Snap-in nut metric, M6, ref. NUT0956 | 4 | NUT0956 |
| 941 | Z 17 | Washer, flat, L6x18 | 4 | L6x18 |
| 942 | Z 18 | Lockwasher, W6 | 4 | W6 |
| 943 | Z 19 | Grounding rivet, pop type, ref. 7240360 | 3 | 7240360 |
| 944 | X 13 | Spacer, snap-in, height 10.5mm, ref.223.01.1024 | 4 | 223.01.1024 |
| 945 | X 14 | Damper, silicone rubber, ref. PARA.80x25x1 | 8 | PARA.80x25x1 |
| | | | | |
| | | | | |