1

HOTONE

BASS PRESS

VOLUME/EXPRESSION/WAH-WAH PEDAL

Owner's Manual

THANK YOU FOR PURCHASING A HOTONE PRODUCT!

www.hotoneaudio.com

PRESS SERIES PEDAL

2



BASS PRESS

VOLUME/EXPRESSION/WAH-WAH PEDAL

- 1.INPUT: 1/4"mono audio jack, for connecting bass.
- 2.MODE selector:
  VOL—Volume mode, for use as volume pedal.
  EXP—Expression mode, for connecting to another device with EXP control IN jack. EXP mode can work without power supply. If the pedal doesn't work, hit the footswitch and try again (without power, the lights will not appear to indicate if the pedal is switched on or off).
  WAH—Wah mode, for use as a wah pedal.
- 3."DC IN": Plug in 9V DC adapter (center negative).

3

BASS PRESS

VOLUME/EXPRESSION/WAH-WAH PEDAL



- 1.OUTPUT: 1/4"mono audio jack, for signal out or expression control out. When used as an expression pedal, it needs a stereo cable with 1/4" stereo plugs at both ends of the cable.
- 2.BOTTOM VALUE: Valid when in VOL and EXP mode. Adjust the control range from 0%~100% to 50%~100%.
- 3.LEDs: Indicates effects or bypass/off status. The pedal is working when LEDs are lit up.
- 4.Footswitch: Switch between effects and bypass/off status.

HOTONE

4

BASS PRESS
VOLUME/EXPRESSION/WAH-WAH PEDAL

Bass Press is a Volume / Expression / Wah 3 in 1 pedal for bass.

Features

- True bypass
- Extreme compact size
- Cool LED lights
- 3 in 1 pedal (Volume, Expression, Wah)
- Specially optimized wah tone for bass
- Adjustable control range (bottom value)
- Active volume mode for lossless tone
- 9V DC or 9V battery power supply

Specifications

Input Impedance (VOL Mode): 1M Ohms
Output Impedance (VOL Mode) : 100 Ohms Current Consumption: Max 20mA
Dimensions: 138mm (D) x 62.5mm (W) x 51mm (H) Weight: 340g