Inward Connections

EQP2 2-Band Parametric Equalizer

Features of this 500 series equalizer:

- Low band frequency range 35Hz to 1KHz
- High band frequency range 560Hz to 16KHz
- Maximum boost/cut +/- 20dB
- Range of bandwidth adjustment 0.16 to 2.0 octave
- Bypass switch
- SPA690 all discrete legendary amp blocks
- Differential balance input transformer less
- Balance output transformer
- Fits standard 500 series slot configuration mechanically and electrically

Specifications:

• Input Impedance	20K ohms balance
• Output Impedance	600 ohms balance
• Frequency Response	+/- 0.5dB@20Hz to 50KHz
• Output Signal to Noise	-95dB or greater
• THD + Noise	.01%@1KHz/+4dBu



Actual size 1.5" x 5.25"

7710 Maestro Avenue, West Hills, CA 91304
tel: 818-883-9012 fax: 818-883-5049
email: sfirlotte@socal.rr.com